
Adafruit FXOS8700 Library Documentation

Release 1.0

Tony DiCola

Jun 07, 2021

Contents

1	Dependencies	3
2	Installing from PyPI	5
3	Usage Example	7
4	Contributing	9
5	Documentation	11
6	Table of Contents	13
6.1	Simple test	13
6.2	adafruit_fxos8700	14
6.2.1	Implementation Notes	14
7	Indices and tables	17
	Python Module Index	19
	Index	21

CircuitPython module for the NXP FXOS8700 accelerometer and magnetometer.

CHAPTER 1

Dependencies

This driver depends on:

- [Adafruit CircuitPython](#)
- [Bus Device](#)

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

CHAPTER 2

Installing from PyPI

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-fxos8700
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-fxos8700
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name  
python3 -m venv .env  
source .env/bin/activate  
pip3 install adafruit-circuitpython-fxos8700
```


CHAPTER 3

Usage Example

```
import time
import board
import adafruit_fxos8700

i2c = board.I2C() # uses board.SCL and board.SDA
sensor = adafruit_fxos8700.FXOS8700(i2c)

while True:
    accel_x, accel_y, accel_z = sensor.accelerometer
    mag_x, mag_y, mag_z = sensor.magnetometer
    print('Acceleration (m/s^2): ({0:0.3f}, {1:0.3f}, {2:0.3f})'.format(accel_x,
↪ accel_y, accel_z))
    print('Magnetometer (uTesla): ({0:0.3f}, {1:0.3f}, {2:0.3f})'.format(mag_x, mag_y,
↪ mag_z))
    time.sleep(1.0)
```


CHAPTER 4

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 5

Documentation

For information on building library documentation, please check out [this guide](#).

6.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/fxos8700_simpletest.py

```
1  # SPDX-FileCopyrightText: 2021 ladyada for Adafruit Industries
2  # SPDX-License-Identifier: MIT
3
4  # Simple demo of the FXOS8700 accelerometer and magnetometer.
5  # Will print the acceleration and magnetometer values every second.
6  import time
7  import board
8  import adafruit_fxos8700
9
10
11 # Create sensor object, communicating over the board's default I2C bus
12 i2c = board.I2C() # uses board.SCL and board.SDA
13 sensor = adafruit_fxos8700.FXOS8700(i2c)
14 # Optionally create the sensor with a different accelerometer range (the
15 # default is 2G, but you can use 4G or 8G values):
16 # sensor = adafruit_fxos8700.FXOS8700(i2c, accel_range=adafruit_fxos8700.ACCEL_RANGE_
17 #   ↳4G)
18 # sensor = adafruit_fxos8700.FXOS8700(i2c, accel_range=adafruit_fxos8700.ACCEL_RANGE_
19 #   ↳8G)
20
21 # Main loop will read the acceleration and magnetometer values every second
22 # and print them out.
23 while True:
24     # Read acceleration & magnetometer.
25     accel_x, accel_y, accel_z = sensor.accelerometer
26     mag_x, mag_y, mag_z = sensor.magnetometer
27     # Print values.
```

(continues on next page)

(continued from previous page)

```

26 print(
27     "Acceleration (m/s^2): ({0:0.3f}, {1:0.3f}, {2:0.3f})".format(
28         accel_x, accel_y, accel_z
29     )
30 )
31 print(
32     "Magnetometer (uTesla): ({0:0.3f}, {1:0.3f}, {2:0.3f})".format(
33         mag_x, mag_y, mag_z
34     )
35 )
36 # Delay for a second.
37 time.sleep(1.0)

```

6.2 adafruit_fxos8700

CircuitPython module for the NXP FXOS8700 accelerometer and magnetometer. Based on the driver from: https://github.com/adafruit/Adafruit_FXOS8700

See examples/simpletest.py for a demo of the usage.

- Author(s): Tony DiCola

6.2.1 Implementation Notes

Hardware:

- Adafruit Precision NXP 9-DOF Breakout Board - FXOS8700 + FXAS21002 (Product ID: 3463)

Software and Dependencies:

- Adafruit CircuitPython firmware for the supported boards: <https://circuitpython.org/downloads>
- Adafruit's Bus Device library: https://github.com/adafruit/Adafruit_CircuitPython_BusDevice

class `adafruit_fxos8700.FXOS8700` (*i2c*, *address=31*, *accel_range=0*)
 Driver for the NXP FXOS8700 accelerometer and magnetometer.

Parameters

- **i2c** (*I2C*) – The I2C bus the device is connected to
- **address** (*int*) – The I2C device address. Defaults to 0x1F
- **accel_range** (*int*) – Device range. Defaults to 0x00.

Quickstart: Importing and using the device

Here is an example of using the `FXOS8700` class. First you will need to import the libraries to use the sensor

```

import board
import adafruit_fxos8700

```

Once this is done you can define your `board.I2C` object and define your sensor object

```

i2c = board.I2C() # uses board.SCL and board.SDA
sensor = adafruit_fxos8700.FXOS8700(i2c)

```

Now you have access to the *accelerometer* and *magnetometer* attributes

```
accel_x, accel_y, accel_z = sensor.accelerometer
mag_x, mag_y, mag_z = sensor.magnetometer
```

accelerometer

Read the acceleration from the accelerometer and return its X, Y, Z axis values as a 3-tuple in m/s^2 .

magnetometer

Read the magnetometer values and return its X, Y, Z axis values as a 3-tuple in μ Teslas.

read_raw_accel_mag()

Read the raw accelerometer and magnetometer readings. Returns a 2-tuple of 3-tuples:

- Accelerometer X, Y, Z axis 14-bit signed raw values
- Magnetometer X, Y, Z axis 16-bit signed raw values

If you want the acceleration or magnetometer values in friendly units consider using the *accelerometer* and *magnetometer* properties!

CHAPTER 7

Indices and tables

- `genindex`
- `modindex`
- `search`

a

`adafruit_fxos8700`, 14

A

`accelerometer` (*adafruit_fxos8700.FXOS8700* attribute), 15
`adafruit_fxos8700` (*module*), 14

F

`FXOS8700` (*class in adafruit_fxos8700*), 14

M

`magnetometer` (*adafruit_fxos8700.FXOS8700* attribute), 15

R

`read_raw_accel_mag()`
(*adafruit_fxos8700.FXOS8700* method), 15