
AdafruitVS1053 Library Documentation

Release 1.0

Tony DiCola

Aug 25, 2020

Contents

1	Dependencies	3
1.1	Installing from PyPI	3
2	Usage Example	5
3	Contributing	7
4	Documentation	9
5	Table of Contents	11
5.1	Simple test	11
5.2	adafruit_vs1053	13
5.2.1	Implementation Notes	13
6	Indices and tables	15
	Python Module Index	17
	Index	19

Driver for interacting and playing media files with the VS1053 audio codec over a SPI connection.

NOTE: This is not currently working for audio playback of files. Only sine wave test currently works. The problem is that pure Python code is currently too slow to keep up with feeding data to the VS1053 fast enough. There's no interrupt support so Python code has to monitor the DREQ line and provide a small buffer of data when ready, but the overhead of the interpreter means we can't keep up. Optimizing SPI to use DMA transfers could help but ultimately an interrupt-based approach is likely what can make this work better (or C functions built in to custom builds that monitor the DREQ line and feed a buffer of data).

CHAPTER 1

Dependencies

This driver depends on:

- [Adafruit CircuitPython](#)
- [Bus Device](#)

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

1.1 Installing from PyPI

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-vs1053
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-vs1053
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name
python3 -m venv .env
source .env/bin/activate
pip3 install adafruit-circuitpython-vs1053
```


CHAPTER 2

Usage Example

See `examples/sdfile_play.py`.

CHAPTER 3

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 4

Documentation

For information on building library documentation, please check out [this guide](#).

5.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/vs1053_simpletest.py

```
1  # Example of sound playback from VS1053 FeatherWing. Can be modified to work
2  # with the breakout by changing the SD card and SPI pins mentioned below.
3  # NOTE:
4  # Unfortunately this doesn't work--the loop isn't fast enough to feed the VS1053
5  # data at the rate it needs for playback. You'll see very erratic behavior with
6  # the VS1053 making static, stopping, and eventually requiring a hard reset.
7  # We'll need to look into interrupt support perhaps to monitor DREQ like in the
8  # arduino library. Basic sine wave playback does however work and monitoring
9  # of attributes like status register and other VS1053 state is accessible.
10 import board
11 import busio
12 import digitalio
13 import storage
14
15 import adafruit_sdcards
16 import adafruit_vs1053
17
18
19 # Define pins connected to VS1053:
20
21 # For FeatherWing with Feather M0:
22 SDCS = board.D5 # Pin connected to SD card CS line.
23 MP3CS = board.D6 # Pin connected to VS1053 CS line.
24 DREQ = board.D9 # Pin connected to VS1053 DREQ line.
25 XDCC = board.D10 # Pin connected to VS1053 D/C line.
26
27
```

(continues on next page)

(continued from previous page)

```

28 # Other configuration:
29 PLAYBACK_FILE = "/sd/test.wav" # Name of file to play.
30 # This should be the full path
31 # including /sd prefix if on
32 # sd card.
33
34 BUFFER_SIZE = 128 # Size in bytes of the MP3 data buffer for sending data to
35 # the VS1053.
36
37
38 # Setup SPI bus (hardware SPI).
39 spi = busio.SPI(board.SCK, MOSI=board.MOSI, MISO=board.MISO)
40
41 # Setup SD card and mount it in the filesystem.
42 sd_cs = digitalio.DigitalInOut(SDCS)
43 sdcard = adafruit_sdcard.SDCard(spi, sd_cs)
44 vfs = storage.VfsFat(sdcard)
45 storage.mount(vfs, "/sd")
46
47 # To list all the files on the SD card root uncomment:
48 # import os
49 # print('SD card root contains:')
50 # print(os.listdir('/sd'))
51
52 # Setup VS1053.
53 vs1053 = adafruit_vs1053.VS1053(spi, MP3CS, XDCS, DREQ)
54
55 # Set volume of left and right channels.
56 # Value ranges from 0 to 255 for each channel, the lower the higher volume.
57 vs1053.set_volume(0, 0)
58
59 # Play a test tone (this works).
60 print("Playing test tone for two seconds...")
61 vs1053.sine_test(0x44, 2.0)
62 print("Done playing tone!")
63
64 # Play back a MP3 file by starting playback, then reading a buffer of data
65 # at a time and sending it to the VS1053.
66 # Unfortunately this doesn't work--the loop isn't fast enough to feed the VS1053
67 # data at the rate it needs for playback. You'll see very erratic behavior with
68 # the VS1053 making static, stopping, and eventually requiring a hard reset.
69 # We'll need to look into interrupt support perhaps to monitor DREQ like in the
70 # arduino library.
71 print("Playing {}".format(PLAYBACK_FILE))
72 vs1053.start_playback()
73 with open(PLAYBACK_FILE, "rb") as infile:
74     music_data = infile.read(BUFFER_SIZE)
75     while music_data is not None and music_data != "":
76         while not vs1053.ready_for_data:
77             pass
78         vs1053.play_data(music_data, end=len(music_data))
79         music_data = infile.read(BUFFER_SIZE)
80
81 print("Done!")

```


5.2 adafruit_vs1053

Driver for interacting and playing media files with the VS1053 audio codec over a SPI connection.

NOTE: This is not currently working for audio playback of files. Only sine wave test currently works. The problem is that pure Python code is currently too slow to keep up with feeding data to the VS1053 fast enough. There's no interrupt support so Python code has to monitor the DREQ line and provide a small buffer of data when ready, but the overhead of the interpreter means we can't keep up. Optimizing SPI to use DMA transfers could help but ultimately an interrupt-based approach is likely what can make this work better (or C functions built in to custom builds that monitor the DREQ line and feed a buffer of data).

- Author(s): Tony DiCola

5.2.1 Implementation Notes

Hardware:

- Adafruit Music Maker FeatherWing - Synth Player
- Music Maker FeatherWing w/ Amp - Synth Player
- VS1053B MP3/WAV/OGG/MIDI Player & Recorder (CODEC) Chip
- VS1053 Codec + MicroSD Breakout - Play + Record - v4

Software and Dependencies:

- Adafruit CircuitPython firmware for the supported boards: <https://github.com/adafruit/circuitpython/releases>
- Adafruit's Bus Device library: https://github.com/adafruit/Adafruit_CircuitPython_BusDevice

class `adafruit_vs1053.VS1053` (*spi, cs, xdc, dreq*)

Class-level buffer for read and write commands.

byte_rate

Return the bit rate in bytes per second (computed each second). Useful to know if a song is being played and how fast it's happening.

decode_time

Return the decode time register value. This is the amount of time the current file has been played back in seconds.

play_data (*data_buffer, start=0, end=None*)

Send a buffer of file data to the VS1053 for playback. Make sure the `ready_for_data` property is `True` before calling!

ready_for_data

Return `True` if the VS1053 is ready to accept data, false otherwise.

reset ()

Perform a longer full reset with clock and volume reset too.

set_volume (*left, right*)

Set the volume of the left and right channels to the provided byte value (0-255), the lower the louder.

sine_test (*n, seconds*)

Play a sine wave for the specified number of seconds. Useful to test the VS1053 is working.

soft_reset ()

Perform a quick soft reset of the VS1053.

start_playback()

Prepare for playback of a file. After calling this check the ready_for_data property continually until true and then send in buffers of music data to the play_data function.

stop_playback()

Stop any playback of audio.

version

Return the status register version value.

CHAPTER 6

Indices and tables

- `genindex`
- `modindex`
- `search`

a

adafruit_vs1053, [12](#)

A

`adafruit_vs1053` (*module*), [12](#)

B

`byte_rate` (*adafruit_vs1053.VS1053 attribute*), [13](#)

D

`decode_time` (*adafruit_vs1053.VS1053 attribute*), [13](#)

P

`play_data()` (*adafruit_vs1053.VS1053 method*), [13](#)

R

`ready_for_data` (*adafruit_vs1053.VS1053 attribute*), [13](#)

`reset()` (*adafruit_vs1053.VS1053 method*), [13](#)

S

`set_volume()` (*adafruit_vs1053.VS1053 method*), [13](#)

`sine_test()` (*adafruit_vs1053.VS1053 method*), [13](#)

`soft_reset()` (*adafruit_vs1053.VS1053 method*), [13](#)

`start_playback()` (*adafruit_vs1053.VS1053 method*), [13](#)

`stop_playback()` (*adafruit_vs1053.VS1053 method*), [14](#)

V

`version` (*adafruit_vs1053.VS1053 attribute*), [14](#)

`VS1053` (*class in adafruit_vs1053*), [13](#)