
Adafruit BME680 Library Documentation

Release 1.0

ladyada

Feb 11, 2021

Contents

1	Dependencies	3
2	Installing from PyPI	5
3	Usage Example	7
4	Contributing	9
5	Documentation	11
6	Table of Contents	13
6.1	Simple test	13
6.2	adafruit_bme680	14
6.2.1	Implementation Notes	14
7	Indices and tables	17
	Python Module Index	19
	Index	21

CircuitPython driver for BME680 sensor over I2C

CHAPTER 1

Dependencies

This driver depends on:

- Adafruit CircuitPython
- Bus Device

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

CHAPTER 2

Installing from PyPI

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-bme680
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-bme680
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name  
python3 -m venv .env  
source .env/bin/activate  
pip3 install adafruit-circuitpython-bme680
```


CHAPTER 3

Usage Example

```
from busio import I2C
import adafruit_bme680
import time
import board

# Create library object using our Bus I2C port
i2c = I2C(board.SCL, board.SDA)
bme680 = adafruit_bme680.Adafruit_BME680_I2C(i2c)

# change this to match the location's pressure (hPa) at sea level
bme680.sea_level_pressure = 1013.25

while True:
    print("\nTemperature: %0.1f C" % bme680.temperature)
    print("Gas: %d ohm" % bme680.gas)
    print("Humidity: %0.1f %%" % bme680.relative_humidity)
    print("Pressure: %0.3f hPa" % bme680.pressure)
    print("Altitude = %0.2f meters" % bme680.altitude)

    time.sleep(2)
```


CHAPTER 4

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 5

Documentation

For information on building library documentation, please check out [this guide](#).

CHAPTER 6

Table of Contents

6.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/bme680_simpletest.py

```
1 # SPDX-FileCopyrightText: 2021 ladyada for Adafruit Industries
2 # SPDX-License-Identifier: MIT
3
4 import time
5 import board
6 from busio import I2C
7 import adafruit_bme680
8
9 # Create library object using our Bus I2C port
10 i2c = I2C(board.SCL, board.SDA)
11 bme680 = adafruit_bme680.Adafruit_BME680_I2C(i2c, debug=False)
12
13 # change this to match the location's pressure (hPa) at sea level
14 bme680.sea_level_pressure = 1013.25
15
16 # You will usually have to add an offset to account for the temperature of
17 # the sensor. This is usually around 5 degrees but varies by use. Use a
18 # separate temperature sensor to calibrate this one.
19 temperature_offset = -5
20
21 while True:
22     print("\nTemperature: %0.1f C" % (bme680.temperature + temperature_offset))
23     print("Gas: %d ohm" % bme680.gas)
24     print("Humidity: %0.1f %%" % bme680.relative_humidity)
25     print("Pressure: %0.3f hPa" % bme680.pressure)
26     print("Altitude = %0.2f meters" % bme680.altitude)
```

(continues on next page)

(continued from previous page)

28 time.sleep(1)

6.2 adafruit_bme680

CircuitPython library for BME680 temperature, pressure and humidity sensor.

- Author(s): Limor Fried

6.2.1 Implementation Notes

Hardware:

- Adafruit BME680 Temp, Humidity, Pressure and Gas Sensor

Software and Dependencies:

- Adafruit CircuitPython firmware for the supported boards: <https://github.com/adafruit/circuitpython/releases>
- Adafruit's Bus Device library: https://github.com/adafruit/Adafruit_CircuitPython_BusDevice

class adafruit_bme680.**Adafruit_BME680** (*, refresh_rate=10)

Driver from BME680 air quality sensor

Parameters **refresh_rate** (*int*) – Maximum number of readings per second. Faster property reads will be from the previous reading.

altitude

The altitude based on current pressure vs the sea level pressure (`sea_level_pressure`) - which you must enter ahead of time)

filter_size

The filter size for the built in IIR filter

gas

The gas resistance in ohms

humidity

The relative humidity in RH %

humidity_oversample

The oversampling for humidity sensor

pressure

The barometric pressure in hectoPascals

pressure_oversample

The oversampling for pressure sensor

relative_humidity

The relative humidity in RH %

sea_level_pressure = None

Pressure in hectoPascals at sea level. Used to calibrate altitude.

temperature

The compensated temperature in degrees celsius.

temperature_oversample

The oversampling for temperature sensor

```
class adafruit_bme680.Adafruit_BME680_I2C(i2c, address=119, debug=False, *, refresh_rate=10)
```

Driver for I2C connected BME680.

Parameters

- **address** (*int*) – I2C device address
- **debug** (*bool*) – Print debug statements when True.
- **refresh_rate** (*int*) – Maximum number of readings per second. Faster property reads will be from the previous reading.

```
class adafruit_bme680.Adafruit_BME680_SPI(spi, cs, baudrate=100000, debug=False, *, refresh_rate=10)
```

Driver for SPI connected BME680.

Parameters

- **spi** (*busio.SPI*) – SPI device
- **cs** (*digitalio.DigitalInOut*) – Chip Select
- **debug** (*bool*) – Print debug statements when True.
- **baudrate** (*int*) – Clock rate, default is 100000
- **refresh_rate** (*int*) – Maximum number of readings per second. Faster property reads will be from the previous reading.

CHAPTER 7

Indices and tables

- genindex
- modindex
- search

Python Module Index

a

adafruit_bme680, 14

A

Adafruit_BME680 (*class in adafruit_bme680*), 14
adafruit_bme680 (*module*), 14
Adafruit_BME680_I2C (*class in adafruit_bme680*), 14
Adafruit_BME680_SPI (*class in adafruit_bme680*), 15
altitude (*adafruit_bme680.Adafruit_BME680 attribute*), 14

F

filter_size (*adafruit_bme680.Adafruit_BME680 attribute*), 14

G

gas (*adafruit_bme680.Adafruit_BME680 attribute*), 14

H

humidity (*adafruit_bme680.Adafruit_BME680 attribute*), 14
humidity_oversample (*adafruit_bme680.Adafruit_BME680 attribute*), 14

P

pressure (*adafruit_bme680.Adafruit_BME680 attribute*), 14
pressure_oversample (*adafruit_bme680.Adafruit_BME680 attribute*), 14

R

relative_humidity (*adafruit_bme680.Adafruit_BME680 attribute*), 14

S

sea_level_pressure (*adafruit_bme680.Adafruit_BME680 attribute*), 14

T

temperature (*adafruit_bme680.Adafruit_BME680 attribute*), 14
temperature_oversample (*adafruit_bme680.Adafruit_BME680 attribute*), 14