
AdafruitOneWire Library Documentation

Release 1.0

Carter Nelson

Sep 24, 2021

Contents

1	Dependencies	3
2	Usage Example	5
3	Contributing	7
4	Documentation	9
5	Table of Contents	11
5.1	Simple test	11
5.2	adafruit_owewire.bus	12
5.3	adafruit_owewire.device	13
6	Indices and tables	15
	Python Module Index	17
	Index	19

Classes for use in communicating with devices on a 1-Wire bus.

CHAPTER 1

Dependencies

This driver depends on:

- [Adafruit CircuitPython](#)

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

Note: This library does **not** work on the Raspberry Pi as there is no kernel interface for it

CHAPTER 2

Usage Example

```
import board
from adafruit_owewire.bus import OneWireBus
ow_bus = OneWireBus(board.D2)
devices = ow_bus.scan()
for d in devices:
    print("ROM={}\tFamily=0x{:02x}".format(d.rom, d.family_code))
```


CHAPTER 3

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 4

Documentation

For information on building library documentation, please check out [this guide](#).

5.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/onewire_simpletest.py

```
1 # SPDX-FileCopyrightText: 2021 ladyada for Adafruit Industries
2 # SPDX-License-Identifier: MIT
3
4 import board
5 from adafruit_onewire.bus import OneWireBus
6
7 # Create the 1-Wire Bus
8 # Use whatever pin you've connected to on your board
9 ow_bus = OneWireBus(board.D2)
10
11 # Reset and check for presence pulse.
12 # This is basically - "is there anything out there?"
13 print("Resetting bus...", end="")
14 if ow_bus.reset():
15     print("OK.")
16 else:
17     raise RuntimeError("Nothing found on bus.")
18
19 # Run a scan to get all of the device ROM values
20 print("Scanning for devices...", end="")
21 devices = ow_bus.scan()
22 print("OK.")
23 print("Found {} device(s)".format(len(devices)))
24
25 # For each device found, print out some info
26 for i, d in enumerate(devices):
27     print("Device {:>3}".format(i))
```

(continues on next page)

(continued from previous page)

```

28 print("\tSerial Number = ", end="")
29 for byte in d.serial_number:
30     print("0x{:02x} ".format(byte), end="")
31 print("\n\tFamily = 0x{:02x}".format(d.family_code))
32
33 # Usage beyond this is device specific. See a CircuitPython library for a 1-Wire
34 # device for examples and how OneWireDevice is used.

```

5.2 adafruit_owewire.bus

Provide access to a 1-Wire bus.

- Author(s): Carter Nelson

class `adafruit_owewire.bus.OneWireAddress` (*rom*)

A class to represent a 1-Wire address.

crc

The 8 bit CRC.

family_code

The 8 bit family code.

rom

The unique 64 bit ROM code.

serial_number

The 48 bit serial number.

class `adafruit_owewire.bus.OneWireBus` (*pin*)

A class to represent a 1-Wire bus.

static crc8 (*data*)

Perform the 1-Wire CRC check on the provided data.

Parameters *data* (*bytearray*) – 8 byte array representing 64 bit ROM code

maximum_devices

The maximum number of devices the bus will scan for. Valid range is 1 to 255. It is an error to have more devices on the bus than this number. Having less is OK.

readinto (*buf*, *, *start=0*, *end=None*)

Read into *buf* from the device. The number of bytes read will be the length of *buf*.

If *start* or *end* is provided, then the buffer will be sliced as if `buf[start:end]`. This will not cause an allocation like `buf[start:end]` will so it saves memory.

Parameters

- **buf** (*bytearray*) – buffer to write into
- **start** (*int*) – Index to start writing at
- **end** (*int*) – Index to write up to but not include

reset (*required=False*)

Perform a reset and check for presence pulse.

Parameters **required** (*bool*) – require presence pulse

scan()

Scan for devices on the bus and return a list of addresses.

write (*buf*, *, *start=0*, *end=None*)

Write the bytes from *buf* to the device.

If *start* or *end* is provided, then the buffer will be sliced as if `buffer[start:end]`. This will not cause an allocation like `buffer[start:end]` will so it saves memory.

Parameters

- **buf** (*bytearray*) – buffer containing the bytes to write
- **start** (*int*) – Index to start writing from
- **end** (*int*) – Index to read up to but not include

exception `adafruit_owewire.bus.OneWireError`

A class to represent a 1-Wire exception.

5.3 `adafruit_owewire.device`

Provides access to a single device on the 1-Wire bus.

- Author(s): Carter Nelson

class `adafruit_owewire.device.OneWireDevice` (*bus*, *address*)

A class to represent a single device on the 1-Wire bus.

readinto (*buf*, *, *start=0*, *end=None*)

Read into *buf* from the device. The number of bytes read will be the length of *buf*.

If *start* or *end* is provided, then the buffer will be sliced as if `buf[start:end]`. This will not cause an allocation like `buf[start:end]` will so it saves memory.

Parameters

- **buf** (*bytearray*) – buffer to write into
- **start** (*int*) – Index to start writing at
- **end** (*int*) – Index to write up to but not include

write (*buf*, *, *start=0*, *end=None*)

Write the bytes from *buf* to the device.

If *start* or *end* is provided, then the buffer will be sliced as if `buffer[start:end]`. This will not cause an allocation like `buffer[start:end]` will so it saves memory.

Parameters

- **buf** (*bytearray*) – buffer containing the bytes to write
- **start** (*int*) – Index to start writing from
- **end** (*int*) – Index to read up to but not include

CHAPTER 6

Indices and tables

- `genindex`
- `modindex`
- `search`

Python Module Index

a

`adafruit_owewire.bus`, [12](#)

`adafruit_owewire.device`, [13](#)

A

`adafruit_owewire.bus` (module), 12
`adafruit_owewire.device` (module), 13

C

`crc` (*adafruit_owewire.bus.OneWireAddress* attribute), 12
`crc8()` (*adafruit_owewire.bus.OneWireBus* static method), 12

F

`family_code` (*adafruit_owewire.bus.OneWireAddress* attribute), 12

M

`maximum_devices` (*adafruit_owewire.bus.OneWireBus* attribute), 12

O

`OneWireAddress` (class in *adafruit_owewire.bus*), 12
`OneWireBus` (class in *adafruit_owewire.bus*), 12
`OneWireDevice` (class in *adafruit_owewire.device*), 13
`OneWireError`, 13

R

`readinto()` (*adafruit_owewire.bus.OneWireBus* method), 12
`readinto()` (*adafruit_owewire.device.OneWireDevice* method), 13
`reset()` (*adafruit_owewire.bus.OneWireBus* method), 12
`rom` (*adafruit_owewire.bus.OneWireAddress* attribute), 12

S

`scan()` (*adafruit_owewire.bus.OneWireBus* method), 12
`serial_number` (*adafruit_owewire.bus.OneWireAddress* attribute), 12

W

`write()` (*adafruit_owewire.bus.OneWireBus* method), 13
`write()` (*adafruit_owewire.device.OneWireDevice* method), 13