
AdafruitTrellisM4 Library Documentation

Release 1.0

Scott Shawcroft

Mar 02, 2021

Contents

1	Dependencies	3
1.1	Installing from PyPI	3
2	Usage Example	5
3	Contributing	7
4	Documentation	9
5	Table of Contents	11
5.1	Simple test	11
5.2	adafruit_trellism4	11
5.2.1	Implementation Notes	11
6	Indices and tables	15
	Python Module Index	17
	Index	19

This high level library provides objects that represent Trellis M4 hardware.

CHAPTER 1

Dependencies

This driver depends on:

- [Adafruit CircuitPython](#)

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

1.1 Installing from PyPI

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-trellism4
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-trellism4
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name
python3 -m venv .env
source .env/bin/activate
pip3 install adafruit-circuitpython-trellism4
```


CHAPTER 2

Usage Example

This example prints out the coordinates of a button each time it is pressed and released:

```
import time
import adafruit_trellism4

trellis = adafruit_trellism4.TrellisM4Express()

current_press = set()
while True:
    pressed = set(trellis.pressed_keys)
    for press in pressed - current_press:
        print("Pressed:", press)
    for release in current_press - pressed:
        print("Released:", release)
    time.sleep(0.08)
    current_press = pressed
```


CHAPTER 3

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 4

Documentation

For information on building library documentation, please check out [this guide](#).

5.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/trellism4_simpletest.py

```
1  # SPDX-FileCopyrightText: 2021 ladyada for Adafruit Industries
2  # SPDX-License-Identifier: MIT
3
4  import adafruit_trellism4
5
6  trellis = adafruit_trellism4.TrellisM4Express()
7
8  while True:
9      pressed = trellis.pressed_keys
10     if pressed:
11         print("Pressed:", pressed)
```

5.2 adafruit_trellism4

CircuitPython library for the Trellis M4 Express.

- Author(s): Scott Shawcroft, Kattni Rembor

5.2.1 Implementation Notes

Hardware:

Add link to Trellis M4 Express when product is released.

Software and Dependencies:

- Adafruit CircuitPython firmware for the supported boards: <https://github.com/adafruit/circuitpython/releases>

class adafruit_trellism4.TrellisM4Express (rotation=0)

Represents a single Trellis M4 Express. Do not use more than one at a time.

Parameters **rotation** – Allows for rotating the Trellis M4 Express in 90 degree increments to different positions and utilising the grid from that position. Supports 0, 90, 180, and 270. 0 degrees is when the USB facing away from you. Default is 0.

```
import time
import adafruit_trellism4

trellis = adafruit_trellism4.TrellisM4Express()

current_press = set()
while True:
    pressed = set(trellis.pressed_keys)
    for press in pressed - current_press:
        print("Pressed:", press)
    for release in current_press - pressed:
        print("Released:", release)
    time.sleep(0.08)
    current_press = pressed
```

pixels = None

Sequence like object representing the 32 NeoPixels on the Trellis M4 Express, Provides a two dimensional representation of the NeoPixel grid.

This example lights up the first pixel green:

```
import adafruit_trellism4

trellis = adafruit_trellism4.TrellisM4Express()

trellis.pixels[0, 0] = (0, 255, 0)
```

Options for pixels:

`pixels.fill`: Colors all the pixels a given color. Provide an (R, G, B) color tuple (such as (255, 0, 0) for red), or a hex color value (such as 0xff0000 for red).

This example colors all pixels red:

```
import adafruit_trellism4

trellis = adafruit_trellism4.TrellisM4Express()

trellis.pixels.fill((255, 0, 0))
```

`pixels.width` and `pixels.height`: The width and height of the grid. When rotation is 0, width is 8 and height is 4.

This example colors all pixels blue:

```
import adafruit_trellism4

trellis = adafruit_trellism4.TrellisM4Express()

for x in range(trellis.pixels.width):
```

(continues on next page)

(continued from previous page)

```
for y in range(trellis.pixels.height):  
    trellis.pixels[x, y] = (0, 0, 255)
```

`pixels.brightness`: The overall brightness of the pixel. Must be a number between 0 and 1, where the number represents a percentage between 0 and 100, i.e. 0.3 is 30%.

This example sets the brightness to 0.3 and turns all the LEDs red:

```
import adafruit_trellism4  
  
trellis = adafruit_trellism4.TrellisM4Express()  
  
trellis.pixels.brightness = 0.3  
  
trellis.pixels.fill((255, 0, 0))
```

pressed_keys

A list of tuples of currently pressed button coordinates.

```
import time  
import adafruit_trellism4  
  
trellis = adafruit_trellism4.TrellisM4Express()  
  
current_press = set()  
while True:  
    pressed = set(trellis.pressed_keys)  
    for press in pressed - current_press:  
        print("Pressed:", press)  
    for release in current_press - pressed:  
        print("Released:", release)  
    time.sleep(0.08)  
    current_press = pressed
```


CHAPTER 6

Indices and tables

- `genindex`
- `modindex`
- `search`

a

adafruit_trellism4, [11](#)

A

`adafruit_trellism4` (*module*), [11](#)

P

`pixels` (*adafruit_trellism4.TrellisM4Express* attribute), [12](#)

`pressed_keys` (*adafruit_trellism4.TrellisM4Express* attribute), [13](#)

T

`TrellisM4Express` (*class in adafruit_trellism4*), [12](#)